



AM FM Stereo Tuner SH-F308R

1. High-grade aluminum 1U black brushed panel, rack-mounted, beautiful and elegant;
2. Built-in professional-grade high-fidelity stereo digital quartz phase-locked loop radio system;
3. Manual/automatic/frequency direct input and other tuning systems, ultra-high sensitivity reception;
4. Unique channel browsing and playback function, more than 60 radio frequency storage/lifetime memory, never lost;
5. The output adopts Class AA amplification, the sound quality is more touching, dual 2CH;
6. Leisurely infrared full-function remote control;
7. Dynamic color output level spectrum display, ten fantasy spectrum display modes to choose from;
8. Antenna input: 75ohms;
9. Audio output: <math>< 500\text{mV}</math>, 10Kohms(Ω), unbalanced;
10. Frequency range: AM: 522KHz~1620KHz FM: 87MHz~108MHz;
11. Distortion: <math>< 0.01\%</math> at 1KHz;
12. Signal-to-noise ratio: AM: >40dB FM: >45dB;
13. Frequency response: 20Hz~18KHz;
14. Power cord: (3×0.5 mm²)×1.5M (standard);
15. Power supply: AC220V±10% 50~60Hz;
16. Power consumption: 10~15W;
17. Overall dimensions: 51×483×255mm;
18. Net weight: 2.3kg

Web: www.koontech.com

Email: marketing@koontech.com

Tel: (HK Office) +852 9068 2799 / (Shenzhen Office) +86 755 2744 8753

Shenzhen Office: T3 1001, Yifang Center, Baoan, Shezhen, China

HK Office: Unit C, 2/F, Ka To Factory Building, 2 Cheung Yue Street, Cheung Sha Wan, Kowloon, Hong Kong

Factory: KNTech Building, Phoenix Mountain, Limhai Zone, Shajiao Community, Humen, Dongguan, China