

Channels Selector

Model: KN-6013D



- ※ High-grade aluminum 2U black oxide brushed panel, beautiful and elegant;
- ※ 2-channel input, 10-zone output (70V/100V audio signal);
- ※ 10 channel partitions can be arbitrarily selected;
- ※ 25-pin computer activation interface, 10-channel alarm input;
- ※ Background music and emergency broadcast switching do not affect each other;
- ※ 10 output channel strobe LED indication;
- ※ Adopt DC24V and AC100~240V dual power supply, automatically switch to DC24 DC power supply when there is no mains input;
- ※ Group A input: 70V/100V, audio signal;
- ※ Group B input: 70V/100V, emergency broadcast (alarm) audio signal;
- ※ The number of controllable partitions: ten areas 'CH1~CH10' (emergency broadcast (alarm) audio signal is activated and output by the alarm signal);
- ※ Controlled partition output capacity: the total audio signal input capacity: 1 kW; the output of each partition can be assigned an average load capacity of 100 W;
- ※ Channel switching capability: 500 W, audio signal;
- ※ Alarm activation input: (0V) short circuit signal, (ALARM IN);
- ※ Alarm activation output: (0V) short circuit signal two, (ALARM OUT);
- ※ Power cord: (3×0.75 mm²)×1.5M (standard);
- ※ Power supply: AC 220V±10% 50-60Hz;
- ※ Power consumption: 10~15W;
- ※ Machine size: 89(H)×483(W)×350(D)mm;
- ※ Net weight: 6.34kg;